

Fixture Type:	
Model Number:	
Project:	

Lamp Chart

VOLTS	WATTS	LAMP TYPE	ORDER CODE	LAMP #
6	3.6	Wedge Base Incandescent	15	909
6	5.4	Wedge Base Incandescent	14	939
6	7.2	Wedge Base Incandescent	01	927
6	8	PAR 36 Sealed Beam	02	7613
6	8	PAR 36 Halogen Sealed Beam	03	H7551
6	9	Wedge Base Incandescent	04	908
6	12	PAR 36 Sealed Beam	05	4042
6	12	PAR 36 Halogen Sealed Beam	06	H7553
6	18	PAR 36 Sealed Beam	07	4014
6	20	PAR 36 Halogen Sealed Beam	20	H7554
6	25	PAR 36 Sealed Beam	08	4510
6	20	Bipin Halogen	24	788
6	5	Bi-Pin MR16	X	
6	10	Bi-Pin MR16	Y	
6	12	Bi-Pin MR16	Z	
12	8	PAR 36 Halogen Sealed Beam	16	H7555
12	9	Wedge Base Incandescent	09	915
12	12	Wedge Base Incandescent	17	912
12	12	PAR 36 Sealed Beam	10	4044
12	12	PAR 36 Halogen Sealed Beam	11	H7557
12	18	PAR 36 Sealed Beam	12	4414
12	25	PAR 36 Sealed Beam	13	4446
12	37.5	PAR 36 Halogen Sealed Beam	18	H7616
12	50	PAR 36 Sealed Beam	19	H7606
12	12	Bi-Pin MR16	S	
12	16	Bi-Pin MR16	T	
12	6.5	LED-MR16 Envelope	L	S9496

To order a specific lamp for a unit, simply add the order code designator as a suffix to the model number.
For example: CX2-654-05.

Notes: Total lamp wattage cannot exceed total unit capacity.
Other lamps available, consult factory.